

METHOD AND APPARATUS FOR FINDING OPTIMAL UNIFICATION  
SUBSTITUTION FOR FORMULAS IN TECHNOLOGY LIBRARY

ABSTRACT

The present invention is directed to a method and apparatus to find an optimal unification substitution for formulas in a technology library. In an exemplary aspect of the present invention, a method for finding an optimal unification substitution for formulas in a technology library during integrated circuit design may include the following steps: (a) receiving input including a list  $L$  of pairs of formulas in standard form, a set  $S$  of substitutions for variables, a right part  $e(x_1, \dots, x_p)$  of an identity, and an information  $I = \{t, h, r, a, p\}$  on best application; (b) when the list  $L$  is not empty, extracting and removing first pair  $(f'(A'_1, \dots, A'_n), g'(B'_1, \dots, B'_m))$  from the list  $L$ ; (c) removing head inverters and buffers from formulas  $f'(A'_1, \dots, A'_n)$  and  $g'(B'_1, \dots, B'_m)$  and obtaining a pair  $(f(A_1, \dots, A_n), g(B_1, \dots, B_m))$ ; (d) when the  $f$  is a commutative operation but neither a variable nor constant, and when heads of the formulas  $f(A_1, \dots, A_n)$  and  $g(B_1, \dots, B_m)$  are equal, searching for a basic argument  $A_j$  of the formula  $f(A_1, \dots, A_n)$ ; (e) when the basic argument  $A_j$  is found, letting  $P$  be head of said  $A_j$  and setting  $i = 1$ ; (f) when head of  $B_i$  is equal to the  $P$ , making copy  $L'$  of the list  $L$  and making copy  $S'$  of the set  $S$ ; and (g) forming a reduced pair  $(A', B')$  for pairs  $(f(A_1, \dots, A_n), f(B_1, \dots, B_n))$  and  $(A_j, B_i)$  and adding the pairs  $(A_j, B_i)$  and  $(A', B')$  to the list  $L'$ .